

LabSat Real-Time

Generate real-time GNSS RF signals for your test regime with a current time stamp anywhere in the world.

- GPS/Galileo, GLONASS or BeiDou
- Real-time generation of RF signals
- SatGen software included
- Realistic carrier to noise levels
- Single or dual constellation
- Configurable noise levels and signals



Why use a real-time GNSS simulator?

By connecting a real-time simulator to your device it allows you to test GNSS RF signals with a current time stamp simulated from anywhere in the world. You can test specific trajectories and geographical locations with realistic carrier to noise levels and signals all in real-time.

By using a powerful PC with **SatGen** simulation software installed you can generate GPS/Galileo, GLONASS, BeiDou L1 signals in single constellation (1 or 2 bit) or dual constellation signals at 1 bit each.

How does it work?

SatGen software generates a live signal stream to a **LabSat Real-Time** unit. The unit then converts the RF data from digital to analogue with less than 1 second latency.

If you have an NMEA or KML file of your route, you can simply import this directly into your software. You can also create a scenario either by creating a route in Google Maps, or by building a unique trajectory using simple user-defined commands.



LabSat Real-Time variants

The LabSat Real-Time comes in two variants to suit different user requirements:

- **LabSat Real-Time - Record and Replay**
Dual constellation (GPS/Galileo, GLONASS, BeiDou)
- **LabSat Real-Time - Replay only**
Dual constellation (GPS/Galileo, GLONASS, BeiDou)



Product Specifications

| | |
|-------------------------------|--|
| Constellations | GPS L1, GLONASS L1, BeiDou B1, Galileo E1 |
| Output Signal Level | Fixed -83 dBm Ability to vary the C/No levels for all or individual satellites during simulation |
| RF Channels | 2 |
| RF Channel Centre Frequencies | Selectable |
| Number of Satellites Observed | All in view |
| Sampling Frequency | 16.368 MHz |
| Quantisation | 1 or 2 bit (I & Q) |
| Data Format | I & Q |
| Media Storage Included | External hard disk only |
| Active Antenna Voltage Supply | 3.3V |
| Reference Oscillator | 10 MHz OCXO Temperature Stability +/- 0.05 ppm Frequency Stability +/- 0.3 ppm over first year |
| Operating Voltage | 8V to 30 VDC |

